





SKM 565

RF Wireless Systems | evolution wireless 

Cat. No. 021635

General Description


A truly professional stage microphone, the super-cardioid SKM 565  hand-held transmitter sets new standards in quality and sound. It can be combined with any of the receivers from the ew 500  Series or the EM 550 . The SKM 565  features nine frequency banks with up to 20 directly accessible presets each – ready for immediate use.



Technical Data

RF frequency range	518–866 MHz
Transmission frequencies	1,440
Presets.....	max. 20
Switching bandwidth.....	36 MHz
Peak deviation.....	± 48 kHz
Compander	HDX
AF frequency response.....	40–18,000 Hz
Signal-to-noise ratio.....	> 115 dB(A)
THD.....	< 0.9 %
In compliance with....	ETS 300422, ETS 300445, CE , FCC
Power supply.....	2 x 1.5 V (AA)
RF output power	30 mW
Operating time.....	> 8 hrs
Dimensions	d = 50 mm, l = 225 mm
Weight	450 g
Transducer	condenser
AF sensitivity.....	3 mV/Pa
Max. SPL	144 dB
Pick-up pattern	super-cardioid






Features

- 1,440 tunable UHF frequencies for interference-free reception
- Absolutely reliable transmission and extended range due to high RF output power
- Pilot tone squelch for eliminating RF interference
- Rugged metal housing
- Backlit display (lights up when a button is pushed)
- User-friendly menu operation
- Lock function avoids accidental changing of settings
- HDX compander for crystal-clear sound
- 4-step battery status display, also transmitted to receiver
- Mute function
- Wide range of accessories adapts the hand-held transmitter to any requirement
- Delivery includes: 1 SKM 565  hand-held transmitter (condenser, super-cardioid)
 - 1 MZQ 1 microphone clip
 - 1 protective pouch
 - 2 batteries

Recommended Accessories

- | | |
|-------------------------------------|-----------------|
| ■ CC 2 system case | Cat. No. 009826 |
| ■ MZW 1 foam windshield, anthracite | Cat. No. 004839 |
| ■ BA 2015 accu pack | Cat. No. 009950 |
| ■ L 2015 charging unit | Cat. No. 009828 |

Product Variants

- | | |
|---|-----------------|
| ■ SKM 565  -A: Frequency range 518–554 MHz | Cat. No. 009777 |
| ■ SKM 565  -B: Frequency range 626–662 MHz | Cat. No. 009778 |
| ■ SKM 565  -C: Frequency range 740–776 MHz | Cat. No. 009779 |
| ■ SKM 565  -D: Frequency range 786–822 MHz | Cat. No. 009780 |
| ■ SKM 565  -E: Frequency range 830–866 MHz | Cat. No. 009781 |

Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>