

Detector Base Series ECO1000

ECO1000BR1000

- **Suitable for automatic detectors in conventional technology**
- **Screw terminals for secure connection of multiple wires**
- **Terminals for connection of remote indicator**
- **Test contact for examining the detector line without detectors**
- **Mechanical theft protection can be activated**



Description

The Detector Base ECO1000BR1000 is designed for the easy connection of automatic detectors Series ECO1000 in addressable conventional technology. Due to its robust multi-wire screw terminals, the detectors can be wired with ease, thus achieving a secure and durable connection.

The base provides the possibility to easily connect an external remote indicator, and has been designed for surface mounting in dry rooms. For special applications a range of accessories (for moist room, false ceiling or flush installation) is available.

During construction work (or when the detector has been removed) the detector line can be connected through via an auxiliary contact, which is integrated into the base. With that, the whole wiring of the detector line can be examined without risking contamination of the detectors. The contact is automatically opened by installing the detector.

A mechanical theft protection of the detector can optionally be activated at the detector base.

Specifications

Ambient temperature	-30°C to +70°C
Relative humidity	5 – 95% (no condensation)
Dimensions $\varnothing \times H$	102.5 \times 21 (mm)
Colour	white
Weight	44g
Order number	246140
Order name	Detector Base/Conv./1000/SS ECO1000BR1000

Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>