

# PORTFOLIO™

## HOUSING

7"

HD7250QT4  
HD7500QT4



### 7" High Wattage Quartz Downlight T4Q E11

High wattage T4 E11 quartz downlight for higher ceilings. Narrow, medium, and wide distribution. Trim includes upper reflector and lower shielding cone. Lamp socket heat sink assembly attaches to upper reflector maintaining proper focus for different lamp wattages and beam distributions. Lamp replacement can be performed from above or below the ceiling.

Dimensions	Length	Width	Height	Cutout
Standard Housing	18-1/8"	18"	13-3/8"	8-1/8"
Chicago Plenum	18-1/8"	18"	13-3/8"	

#### HOUSING

HD7250QT4=150/250W T4 Quartz Straight Downlight  
HD7250QT4CP=150/250W T4 Quartz Straight Downlight, Chicago Plenum  
HD7500QT4=400/500W T4 Quartz Straight Downlight  
HD7500QT4CP=400/500W T4 Quartz Straight Downlight, Chicago Plenum

#### OPTIONS

DR150=DeRated Wattage Label for 150W Maximum  
DR400=DeRated Wattage Label for 400W Maximum

#### ACCESSORIES

H277=Step Down Transformer, 300VA Max  
HB26=C Channel Bar Hanger, 26" Long, Pair  
HB50=C Channel Bar Hanger, 50" Long, Pair  
RMB22=Wood Joist Bar Hanger, 22" Long, Pair  
HSA7=Slope Adapter for 7" Aperture Housings, Specify Slope  
TRM7= Metal Trim Ring, Specify Finish\*  
TRR7=Rimless Trim Ring, White\*  
FK5=Field Installed Fuse Kit, 5 Amp  
\*Not compatible with Self Flange

## TRIM

### Open Downlight

Narrow Beam



#### TRIM


10741=Self Flanged  
10740=Molded Trim Ring, White

#### FINISH

LI=Low Iridescent Clear  
H=Haze  
WMH=Warm Haze  
G=Gold  
WH=Wheat  
B=Black  
W=Gloss White  
GP=Graphite  
GPH=Graphite Haze  
K=Cognac  
KH=Cognac Haze

#### OPTIONS

WF=White Painted Flange (Self Flanged only)



### Open Downlight

Medium Beam



#### TRIM


10751=Self Flanged  
10750=Molded Trim Ring, White

#### FINISH

LI=Low Iridescent Clear  
H=Haze  
WMH=Warm Haze  
G=Gold  
WH=Wheat  
B=Black  
W=Gloss White  
GP=Graphite  
GPH=Graphite Haze  
K=Cognac  
KH=Cognac Haze

#### OPTIONS

WF=White Painted Flange (Self Flanged only)



### Open Downlight

Wide Beam



#### TRIM


10761=Self Flanged  
10760=Molded Trim Ring, White

#### FINISH

LI=Low Iridescent Clear  
H=Haze  
WMH=Warm Haze  
G=Gold  
WH=Wheat  
B=Black  
W=Gloss White  
GP=Graphite  
GPH=Graphite Haze  
K=Cognac  
KH=Cognac Haze

#### OPTIONS

WF=White Painted Flange (Self Flanged only)



#### Ordering Example

Housing, Trim, Accessories and Lamps ordered as separate line items.

Housing

HD7500QT4

Trim

10741LIWF

Accessories

HB26

## Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>